


Self-defense alarm

An intelligent self-defense alarm, when encountering danger or emergency, turn on the switch, A high-decibel alarm sounded immediately at the scene, and the APP will send the location to the emergency contact.



Real-time positioning



Smart APP




high decibel alarm



SOS

dual alarm

Specification




Connect Network

Download APP

Search for "Tuya Smart" App on Google Play or Apple App Store to download the app



Tuya Smart




Tuya Smart
Open the "Tuya Smart" APP, register a new account or log in with your existing account




Pair the device with the phone

Turn on Bluetooth on your phone before pairing the device with the phone, the "Smart Tuya" application allows adding in an account Multiple devices.


1 Click the "Add Device" or "+" button In the application.




2 Select "Auto Discovery".



3 Move the device close to the phone, press and hold the SOS button until the device's red and green lights flash alternately. The application will automatically detect the device, click "Next" to complete the pairing.



4 Click "Next" to complete the pairing



After the connection is successful, disconnect the Bluetooth of the mobile phone, the device will sound a drop-out alarm; therefore, if you do not use the device for a period of time, please remove the device from the APP; otherwise, directly turn off the Bluetooth of the mobile phone, and the device will continue Sound an alarm

Function

1. Distribution network

Press and hold the SOS button for 5s to enter the network configuration state, the red and green lights flash alternately; if the network has been configured before, remove the device and restart Network distribution, the timeout period is 60 seconds.

2. SOS button

Double-click the alarm, the default silent alarm, you can configure the alarm mode on the APP, divided into silent alarm, sound alarm, Flashing light alarm and sound and light alarm.

3. latch alarm

Pull the latch to alarm, the alarm type defaults to sound alarm; the alarm mode can be configured on the APP, divided into Sound alarm, flashing light alarm and sound and light alarm; restore the latch to stop the alarm.

4. status indicator description

Steady white light: charging, full off when off; flashing green light: Bluetooth is connected; Red light flashes: Bluetooth is not connected.

5. LED lighting

Press once to turn on, press again to turn off, the default is always on; you can set the lighting type on the APP, always on, Slow flash, fast flash.

6. low battery indicator


The red light flashes slowly 5 times, and the APP pushes a low battery reminder;

7. Bluetooth disconnect reminder

When it is detected that the Bluetooth connection between the device and the mobile phone is disconnected, the red light will flash 5 times quickly, and the buzzer will Beeps 5 times, and the APP pushes a disconnect reminder;

8. Emergency notification settings (need to be purchased separately)

In "Settings" in the lower right corner of the main interface, set to send SMS and phone reminders to emergency contacts.



Specification

Size: 70mm*36mm*17mm	Weight: 30g
Alarm decibel: 130dB	Battery: Lithium battery 130mAh
Charging time: 25min	Material: ABS+PC
System: Andriod4.3+ or IOS 8.0+	Bluetooth: 4.0+

FAQ

What is the effective distance between the phone and the device?

The effective distance is determined by the environment. In an open environment (non-obstacles), the maximum can reach 50 meters. In the office or at home, there are walls or other obstacles. The distance will be shorter, about 10-20 meters

How can I add various devices to a mobile phone?

Android supports devices according to different brands. IOS supports "12 devices".

How to unbind the device from the mobile phone?

Click the upper right corner to enter the device settings, and then click "Remove Device" to unbind

How to share the device with others?

Please follow the steps below:

1. Confirm that the added person has a Tuya Smart App account.
2. Find the "Shared Device" option and click "Add Share"
3. Enter his account to finish sharing.

Precautions

1. Support Tuya Smart and Smart Life APP (hereinafter referred to as APP);
2. The APP needs to be kept alive at the mobile phone system level, allowing positioning permissions and allowing self-starting permissions;
3. The SMS and phone push functions need to be purchased in the APP, and the phone number of the emergency contact can be set;
4. Be careful not to actively kill the APP, otherwise it will cause the device to disconnect from the mobile phone and fail to report data;
5. The mobile phone positioning needs to be turned on so that the APP can obtain the current positioning information of the mobile phone when the device alarms;
6. The device has a low battery reminder function, and pay attention to charging the device in time after low battery;
7. The device and the mobile phone are connected via Bluetooth, and the outdoor distance is about 30-50 meters. Exceeding it will cause disconnection and failure.